

Electrical Signaling

Electrical protective signaling systems are configurations of components used to produce alarm signals indicative of fire, smoke, sprinkler waterflow or other emergency and to produce supervisory signals indicative of conditions needing attention with respect to protection equipment or watch service. System configurations are classified according to where and how the signals are received. The categories are commonly designated as local, municipal, remote station, proprietary, emergency voice/alarm communication, emergency communication, and central station. Auxiliary systems are either local or proprietary systems interconnected with a municipal system.

This category presents the major system component categories and the integrated system configurations. The selection of components to form a hybrid system should be made only by those skilled in system design. Also, the suitability of any system application should be judged on the basis of the hazard(s) being protected.

Alarm Signal Initiating Devices

Alarm signals are initiated either automatically or manually. Automatic detectors respond to changes in characteristic phenomena associated with fire or other emergency conditions.

Fire Detection, Smoke-Actuated

FM Approved smoke actuated devices respond to airborne particulate products of combustion.

The photoelectric principle is based on the change in current which accompanies a change in light intensity on a photoelectric cell as a result of smoke entering the detector.

The beam type version has the light source and photoelectric cell separated in the protected area.

The ionization type detector ionizes the air in special chambers within the detector.

Particles entering the exposed chamber decrease the normal ionization current.

Air-sampling detectors have ambient air drawn from the protected area into a chamber containing the sensing element.

Air duct smoke detectors are for the primary purpose of controlling blowers and dampers of air conditioning and ventilating systems to prevent distribution of smoke and gaseous products;

they should not be used as a substitute for open area detection.

Unless otherwise indicated in the listing, the permissible air velocity range for duct type detectors is 250 to 1500 ft/min (75 to 455 m/min) and up to 300 ft/min (90 m/min) for open area detectors.

A "smoke switch" is fail-safe in that loss of power to the device causes the same switching operation as when smoke is detected.

Average coverage should not exceed 900 ft² (84 m²) per detector. Reduced coverage is recommended beneath high ceilings and for high air flow areas such as computer rooms.

These devices are suitable for use in ambients of 32°-100°F (0°-38°C) unless otherwise indicated in the listing. Installation, testing, and maintenance by trained personnel are recommended.

Fire Detectors-Smoke

Photoelectric Type Smoke Detector, Models SLV-24, SLV-24N or SLV-24V

Photoelectric Type Smoke Detector. SLV-24, SLV-24N or SLV-24V used with NS6 series, NS4 series or HSC-Relay series 2-wire bases or HSC-4R 4-wire bases. Rated voltage is 15 to 33Vdc. The SLV-24 and SLV-24N respond to smoke levels corresponding to 0.5 to 3.8%/ft. (1.64 to 12.47%/m). The SLV-24V responds to smoke levels corresponding to 0.5 to 2.68%/ft. (1.64 to 8.79%/m) and is suitable for installation in air velocities up to 4000ft./min.

Company Name:	Hochiki America Corp
Company Address:	7051 Village Dr, Suite 100, Buena Park, California 90621, USA
Company Website:	http://www.hochiki.com
New/Updated Product Listing:	No
Listing Country:	United States of America
Certification Type:	FM Approved