

## 8 CHANNEL RELAY PANEL MODULE



### STANDARD FEATURES

- Simple 'plug-in' connection to the L@titude Fire Alarm Control Panel
- 8 volt free changeover relay contacts (1 Amp 30V DC)
- Relay operated indications
- All outputs programmable for cause and effects
- Decals provided to redesignate terminals

### DESCRIPTION

The 8 Channel Relay Panel Module has 8 voltage-free changeover relay contacts, each of which can be individually programmed. All outputs are configurable in the same way as devices connected to the loops and all may be acted upon by cause and effect logic. These boards are typically used in applications which require more than the five standard relay outputs, such as signalling to other systems or plant control.

### TECHNICAL SPECIFICATIONS

<b>Supply Voltage Range</b>	24 V DC
<b>Quiescent Current Consumption</b>	10mA
<b>Maximum Current Consumption</b>	160mA (all relay on)
<b>Output Contact Rating</b>	30 VDC 1 Amp
<b>Dimensions</b>	9.25" x 2.5" (234.6mm x 62.8mm)
<b>Cable Capacity</b>	2.5mm per terminal
<b>Operating Temperature</b>	23° F to 120° F ( -5° C to 49° C)
<b>Operating Humidity</b>	to 95% (non condensing)

### PRODUCT LISTINGS



Manufactured by Kentec Electronics Ltd.  
Dartford, DA11 2JL, United Kingdom

*Specifications subject to change without notice.*

Hochiki America Corporation  
7051 Village Drive, Suite 100, Buena Park, CA 90621-2268  
Phone: 714-522-2246 Fax: 714-522-2268  
Technical Support: 800-845-6692 or [technicalsupport@hochiki.com](mailto:technicalsupport@hochiki.com)



Find latest revision at [www.hochiki.com](http://www.hochiki.com)

F0233 05/2019