

## FN-LCD-NYS - SERIAL LCD ANNUNCIATOR



### DESCRIPTION

The FN-LCD-NYS serial annunciator provides a convenient and cost effective remote annunciator solution. Up to 15 FN-LCD-NYS annunciators can be connected to the slave RS-485 port of the FireNET control panel or network annunciator. The FN-LCD-NYS's large 320 character display and navigation buttons are a complete mimic of the FireNET control panel display. The use of a common interface allows the user to easily operate the FN-LCD-NYS as if he were operating the FireNET control panel directly.

Security is established by the use of a password or firefighter's enable key. Designed to be aesthetically pleasing, the FN-LCD-NYS is available in red enclosures. The FN-LCD-NYS can be surface or flush mounted without the need for a trim ring.

### STANDARD FEATURES

- UL 864 9th edition Listed
- New York City Approved
- Large 320 character liquid crystal display (8 line x 40 character) allows viewing of system status
- LED indicators for Fire, Supervisory Alarm, Pre-Alarm, Fire Output Active, AC Power On, On Test, Panel Sounder Silenced, Delay Active, More Events, Point Bypassed, General Trouble, Power Trouble, System Trouble & NAC Trouble
- Same controls as the FireNET fire panel (Panel Sounder Silence, Lamp Test, Re-sound Alarm, Fire Drill, Programmable Function, More Events, More Fire Events, Enter & Exit)
- Up to 15 FN-LCD-NYS serial annunciators may be connected to a FireNET control panel or network annunciator
- Resides on the FireNET slave RS-485 line
- Local piezo sounder for event notification
- Supports user codes & firefighter key to enable access & controls
- Powered by FireNET Aux 24VDC or UL fire listed Aux. 24VDC supply
- Available in red and can be surface or flush mounted
- Built-in help & alarm information screens
- Fire drill function

PRODUCT LISTINGS	
 <p>SIGNALING UL 864, NFPA 70 &amp; 72: Signaling Device LISTED S5694</p>	 <p>COA# 6171</p>

Specifications subject to change without notice.

SPECIFICATIONS	
Current Draw	
Standby:	20mA @ 24VDC
Alarm:	110mA @ 24VDC
Dimensions	
FN-LCD-S	10.88" W x 8.00" H x 1.38" D
Back Box	10.38" W x 7.38" H x 1.25" D
Weight	3.5 lbs
Color	Red
Material	ABS/steel enclosure
Operating Temp.	32°F (0°C) 120°F (49°C)
Relative Humidity	85% RH Non-Condensing
Display	8 line x 40 character LCD (320 characters total)
Network	RS485 port

Continued on back.

# ENGINEERING SPECIFICATION

The contractor shall furnish and install the serial remote annunciator model FN-LCD-NYS, where indicated on the plans. The FN-LCD-S shall connect to the FireNET fire alarm control panel (FACP) or network annunciator (FN-LCD-NYN) RS485 slave bus. The serial remote annunciator shall annunciate on its 320 character display and local buzzer, the condition of its master FireNET FACP. Up to 15 FN-LCD-NYS serial annunciators may be connected together on a single RS-485 FireNET slave bus. The FN-LCD-NYS shall be UL listed and compatible with the Hochiki FireNET control panel, and have surface or flush mount capability.

# WIRING DIAGRAM

