

## HX93 Series Mini-Horn



**HX93 SERIES**

### APPLICATIONS

The HX93 Series mini-horn is a high quality remote signaling appliance that offers dependable remote annunciation. The HX93 is listed for use with both filtered and unfiltered power.

The HX93 a jumper is provided to select either the continuous tone or the temporal 3 evacuation tone.

The HX93 can be used on the same sync circuit (HAVSM Series Sync Module) as other HA Signals. The HX93 appliances are UL 464 listed for use with fire protective systems.



- UL 464 Listed - S3597
- CSFM Listed - 7135-0410:0190

### Product Compliance

- NFPA 72

### STANDARD FEATURES

- Nominal voltage 12VDC and 24VDC
- Jumper for Selectable Temporal 3 or Continuous tone
- Horn Frequency of 3100Hz
- Input terminals supports 12 to 18 gauge wire
- Low Current Consumption
- Textured Finish High Impact Plastic Faceplate
- Available in Fire Alarm Red or Off-White.

### HX93 Series Mini-Horn

Model Number	Part Number
HX93-R	0500-06160
HX93-W	0500-06170

NOTES: The sound output for the temporal 3 tone is rated lower since the time the horn is off is averaged into the sound output rating. While the horn is producing a tone in the temporal 3 mode its sound pressure is the same as the continuous mode.

Model Designations:  
 R = Red faceplate W = Off-white faceplate  
 Operating temperature - Indoor Use Only  
 Indoor: 32° to 120°F (0° to 49° C)

### HX93 Current Ratings

Product	HX93
24VDC	18mA
24VFWR	20mA
12VDC	13mA
12VFWR	17mA

Horn Mode	Minimum dBA @ 10ft., per UL 464 @ 24V	Minimum dBA @ 10ft., per UL 464 12V
Temporal 3	81	78
Continuous	86	83

*Specifications subject to change without notice.*

### Hochiki America Corporation

7051 Village Drive, Suite 100 Buena Park, CA 90621-2268  
 Phone: 714/522-2246 Fax: 714/522-2268  
 Technical Support: 800/845-6692 or technicalsupport@hochiki.com

Find latest revision at [www.hochiki.com](http://www.hochiki.com)

